

*Modasa, company leading in the manufacture of generator sets, presents its product range.*

### Genset Description:

<b>Model name</b>	MP-125I
<b>Engine</b>	PERKINS 1204J-E44TTAG2 (EPA Tier 4F)
<b>Alternator</b>	STAMFORD UCI 274D
<b>Controller</b>	Electronic
<b>Phases</b>	Three-phase/ Single-phase
<b>Voltage Selector</b>	208V-480V/ 240V



**Note:** reference image, may vary depending on accessories

### Genset Rating (≤ 3300 fmsl):

Engine	Alternator	Power		Volt.	Phase	Freq.	PF	Max. Current.
		Prime power	Stand By Power					
1204J-E44TTAG2	UCI 274D	124 KVA / 99 KW	137 KVA / 110 KW	208V	3ph	60Hz	0.8	382 A
1204J-E44TTAG2	UCI 274D	125 KVA / 100 KW	139 KVA / 111 KW	480V	3ph	60Hz	0.8	167 A
1204J-E44TTAG2	UCI 274D	79 KVA / 79 KW	84 KVA / 84 KW	240V	1ph	60Hz	1.0	350 A

### Power definitions:

**Prime Power:** Power available at variable load in lieu of a main power network. Overload of 10% is permitted for 1 hour in every 12 hours of operation.

**Standby Power:** Power available at variable load in the event of main power network failure. No overload is permitted.

The above ratings represent the engine performance capabilities to conditions specified in accordance with ISO 8528.

### Codes & Standards:

The Generator set is designed and manufactured in a facility certified to ISO 9001 standards

Engine: ISO 3046, BS 5514 DIN 6271

Alternator: BS5000, VDE 0530, NEMA MG1-32, IEC34, CSAC22,2-100, ASI 1359

Genset: ISO 8528



**General Specifications:****Engine:**

<b>Model</b>	1204J-E44TTAG2
<b>Cylinders</b>	4 in line
<b>Governor type</b>	ECM
<b>Cycle</b>	4 Stroke
<b>Aspiration</b>	Twin Turbocharged
<b>Fuel</b>	Diesel
<b>Combustion system</b>	Direct injection
<b>Cooling system</b>	Water cooled
<b>Bore</b>	4.1 in
<b>Stroke</b>	5.0 in

<b>System Voltage</b>	12V
<b>Frequency</b>	60Hz
<b>Exhaust gas temperature</b>	986 °F
<b>Displacement</b>	268.5 in3
<b>Compression ratio</b>	16.5:1
<b>Lubricating system capacity</b>	1.85 gallons
<b>Coolant system capacity</b>	5.15 gallons

**Fuel consumption (gallon per hour)**

<b>Speed Engine</b>	1800 RPM
<b>Stand by Power</b>	8.2 gallon per hour
<b>Prime Power</b>	7.4 gallon per hour
<b>75% Prime Power</b>	5.6 gallon per hour

**Aftertreatment system**

<b>Aftertreatment type</b>	DOC/DPF/SCR
<b>Aftertreatment configuration</b>	Engine mounted
<b>DEF tank capacity</b>	7.4 gallon

**Alternator:**

<b>Model</b>	UCI 274D
<b>Insulation system</b>	Class "H"
<b>Excitation system</b>	Separately excited (PMG)
<b>A.V.R voltage regulation</b>	MX341 $\pm$ 1.0%
<b>Protection</b>	IP 23

<b>Number of poles</b>	04
<b>Power factor</b>	0.8
<b>Frequency</b>	60Hz
<b>Winding number</b>	Winding 311
<b>Telephone interference</b>	< 2%

**Features Genset:**

- ♦ Enclosure heavy duty steel, Residential silencer included
- ♦ Enclosure center lifting point, External fuel filling
- ♦ Standard sound attenuation foam, Oil & Coolant Drain Ports
- ♦ Direct flexible engine-alternator coupling
- ♦ Structural steel frame with rubber anti-vibration dampers
- ♦ 180 Gallon double wall sub base fuel tank
- ♦ Capacity for 30 hours of autonomy at 75% load prime
- ♦ ABB 400A 3 pole manual circuit breaker
- ♦ Voltage Selector Krauss & Naimer position (Y-YY-Z)
- ♦ Lockable lug box and Cam-Lock distribution panels
- ♦ Convenience receptacles with individual breakers
  - (2) 120V 20 Amp GFCI duplex outlets - (Nema 5-20R type)
  - (3) 125/250V 50 Amp, 3 pole, twist lock (Non-Nema 6369)
- ♦ 12V battery, connection cables, battery holder
- ♦ 12V/3A battery charger in control panel
- ♦ Battery disconnect switch, electric fuel level meter
- ♦ Emergency stop switch located on outside of enclosure
- ♦ Manuals and electrical diagrams in digital

**Distribution panel (side)**

**Controller Data:**

Equipped with the latest electronic digital control module DSE 7320, it allows the start, control, protection and stop of the generator set in manual and automatic modes. Makes automatic transfer.

**Measurements**

- ◇ Current of the three phases L1, L2, L3
- ◇ Voltage of the three phases L - L and L - N
- ◇ Energy demand KWh, KVAh, KVAh
- ◇ Active Energy KVAh
- ◇ Power factor
- ◇ Frequency
- ◇ Hours of operation
- ◇ Memory of the last 250 events, description, date and time
- ◇ Active Power KW
- ◇ Reactive Power KVA
- ◇ Oil pressure
- ◇ Coolant temperature
- ◇ Generator phase sequence.
- ◇ Turning speed
- ◇ Battery voltage

**Protections**

- ◇ Alarm for maintenance activated configured
- ◇ High engine temperature
- ◇ Low/High frequency
- ◇ Low oil pressure
- ◇ Low/High battery voltage
- ◇ Low/High generator voltage
- ◇ Boot failure
- ◇ Stop failure
- ◇ Negative phase sequence fault
- ◇ Over current fault
- ◇ Overload failure
- ◇ Emergency stop

**Enclosed Genset Dimensions:**

Noise Level  
reference @ 23ft

Máximum  
78 + 2 dBA

Ambient  
50 dBA

Lenght 133.9 in  
Width 45.3 in  
Height 84.7 in  
Weight 6610 lbs (dry)  
Fuel tank 180 gallons (double wall)  
Ø Esc. 2.5 in

**Note:** reference values, request more detail with dimensional drawing

**Application images:**

Connection Cam-Lock Standard



Control panel and breaker (rear side)



Lockable external fuel fill