

Modasa, company leading in the manufacture of generator sets, presents its product range.

Genset Description:

Model name	MP-175I
Engine	PERKINS 1206J-E70TTAG3 (EPA Tier 4F)
Alternator	STAMFORD UCI 274G
Controller	Electronic
Phases	Three-phase/ Single-phase
Voltage Selector	208V-480V/ 240V



Note: reference image, may vary depending on accessories

Genset Rating (≤ 3300 famsl):

Engine	Alternator	Power		Volt.	Phase	Freq.	PF	Max. Current.
		Prime power	Stand By Power					
1206J-E70TTAG3	UCI 274G	174.1 kVA / 139.3 kW	193.4 kVA / 154.7 kW	208V	3ph	60Hz	0.8	537 A
1206J-E70TTAG3	UCI 274G	175 kVA / 140 kW	195 kVA / 156 kW	480V	3ph	60Hz	0.8	235 A
1206J-E70TTAG3	UCI 274G	123.4 kVA / 123.4 kW	134.5 kVA / 134.5 kW	240V	1ph	60Hz	1.0	560 A

Power definitions:

Prime Power: Power available at variable load in lieu of a main power network. Overload of 10% is permitted for 1 hour in every 12 hours of operation.

Standby Power: Power available at variable load in the event of main power network failure. No overload is permitted.

The above ratings represent the engine performance capabilities to conditions specified in accordance with ISO 8528.

Codes & Standards:

The Generator set is designed and manufactured in a facility certified to ISO 9001 standards

Engine: ISO 3046, BS 5514, DIN 6271

Alternator: BS5000, VDE 0530, NEMA MG1-32, IEC34, CSAC22,2-100, ASI 1359

Genset: ISO 8528



General Specifications:**Engine:**

Model	1206J-E70TTAG3	System Voltage	12V
Cylinders	6 in line	Frequency	60Hz
Governor type	ECM	Exhaust gas temperature	896 °F
Cycle	4 Stroke	Displacement	427.7 in3
Aspiration	Twin turbocharged aftercooled	Compression ratio	16.5:1
Fuel	Diesel	Lubricating system capacity	4.2 gallons
Combustion system	Direct injection	Coolant system capacity	8.5 gallons
Cooling system	Water cooled		
Bore	105.0 mm		
Stroke	135.0 mm		
Fuel consumption (gallon per hour)		Aftertreatment system	
Speed Engine	1800 RPM	Aftertreatment type	DOC/DPF/SCR
Stand by Power	11.8 gallon per hour	Aftertreatment configuration	Engine mounted
Prime Power	10.8 gallon per hour	DEF tank capacity	8.4 gallon
75% Prime Power	8.2 gallon per hour		

Alternator:

Model	UCI 274G	Number of poles	04
Insulation system	Class "H"	Power factor	0.8
Excitation system	Separately excited (PMG)	Frequency	60Hz
A.V.R voltage regulation	MX341 \pm 1.0%	Winding number	Winding 311
Protection	IP 23	Telephone interference	< 2%

Features Genset:

- ◇ Enclosure heavy duty steel, Residential silencer included
- ◇ Enclosure center lifting point, External fuel filling
- ◇ Standard sound attenuation foam, Oil & Coolant Drain Ports
- ◇ Direct flexible engine-alternator coupling
- ◇ Structural steel frame with rubber anti-vibration dampers
- ◇ 210 Gallon double wall sub base fuel tank
- ◇ Capacity for 25 hours of autonomy at 75% load prime
- ◇ ABB UL 600A 3 pole manual circuit breaker
- ◇ Voltage Selector Krauss & Naimer position (Y-YY-Z)
- ◇ Terminal blocks and Cam-Lock distribution panels
- ◇ Convenience receptacles with individual breakers
 - (2) 120V 20 Amp GFCI duplex outlets - (Nema 5-20R type)p
 - (3) 125/250V 50 Amp, 3 pole, twist lock (Non-Nema 6369)
- ◇ 12V battery, connection cables, battery holder
- ◇ 12V/3A battery charger in control panel
- ◇ Battery disconnect switch, electric fuel level meter
- ◇ Emergency stop switch located on outside of enclosure
- ◇ Manuals and electrical diagrams in digital

**Distribution panel (side)**

Controller Data:

Equipped with the latest electronic digital control module DSE 7320MKII, it allows the start, control, protection and stop of the generator set in manual and automatic modes. Makes automatic transfer.

Measurements

- ◇ Current of the three phases L1, L2, L3
- ◇ Voltage of the three phases L - L and L - N
- ◇ Energy demand KWh, KVAh, KVArh
- ◇ Active Energy KVAh
- ◇ Power factor
- ◇ Frequency
- ◇ Hours of operation
- ◇ Memory of the last 250 events, description, date and time
- ◇ Active Power KW
- ◇ Reactive Power KVA
- ◇ Oil pressure
- ◇ Coolant temperature
- ◇ Generator phase sequence.
- ◇ Turning speed
- ◇ Battery voltage

Protections

- ◇ Alarm for maintenance activated configured
- ◇ High engine temperature
- ◇ Low/High frequency
- ◇ Low oil pressure
- ◇ Low/High battery voltage
- ◇ Low/High generator voltage
- ◇ Boot failure
- ◇ Stop failure
- ◇ Negative phase sequence fault
- ◇ Over current fault
- ◇ Overload failure
- ◇ Emergency stop

Enclosed Genset Dimensions:



Noise Level
reference @ 23ft

Máximo
79 + 2 dBA

Ambient
50 dBA

Lenght 149.6 in
Width 45.5 in
Height 89.1 in
Weight 7496 lbs (dry)
Fuel tank 210 gallons (double wall)
Ø Esc. 5 in

Note: reference values, request more detail with dimensional drawing

Application images:



Control panel and breaker (rear side)



Lockable external fuel fill



Lockable external DEF fill