

Modasa, company leading in the manufacture of generator sets, presents its product range.

Genset Description:

Model name	MH-30I
Engine	HATZ 3H50TIC (EPA Tier 4F)
Alternator	STAMFORD S0L2-P1
Controller	Electronic
Phases	Three-phase/ Single-phase
Voltage Selector	208V-480V/ 240V



Note: reference image, may vary depending on accessories

Genset Rating (≤ 3300 famsl):

Engine	Alternator	Power		Volt.	Phase	Freq.	PF	Max. Current.
		Prime power	Stand By Power					
3H50TIC	S0L2-P1	31.8 KVA / 25.4 KW	34.8 KVA / 27.8 KW	208V	3ph	60Hz	0.8	96 A
3H50TIC	S0L2-P1	33.4 KVA / 26.7 KW	37.9 KVA / 30.3 KW	480V	3ph	60Hz	0.8	46 A
3H50TIC	S0L2-P1	22 KVA / 22 KW	24.2 KVA / 24.2 KW	240V	1ph	60Hz	1.0	101 A

Power definitions:

Prime Power: Power available at variable load in lieu of a main power network. Overload of 10% is permitted for 1 hour in every 12 hours of operation.

Standby Power: Power available at variable load in the event of main power network failure. No overload is permitted.

The above ratings represent the engine performance capabilities to conditions specified in accordance with ISO 8528.

Codes & Standards:

The Generator set is designed and manufactured in a facility certified to ISO 9001 standards

Engine: ISO 3046, BS 5514, DIN 6271

Alternator: BS5000, VDE 0530, NEMA MG1-32, IEC34, CSAC22,2-100, ASI 1359

Genset: ISO 8528



General Specifications:

Engine:

Model	3H50TIC	System Voltage	12V
Cylinders	3 in line	Frequency	60Hz
Governor type	ECM	Displacement	89.3 in3
Cycle	4 Stroke	Compression ratio	17.5:1
Aspiration	Turbocharged	Lubricating system capacity	3.30 gallons
Fuel	Diesel	Coolant system capacity	1.32 gallons
Combustion system	Direct injection		
Cooling system	Water cooled		
Bore	3.31 in		
Stroke	3.46 in		
Fuel consumption (gallon per hour)			
Speed Engine	1800 RPM	Aftertreatment system	
Prime Power	2.1 gallon per hour	Aftertreatment type	EGR/DOC
75% Prime Power	1.3 gallon per hour		

Alternator:

Model	S0L2-P1	Number of poles	04
Insulation system	Class "H"	Power factor	0.8
Excitation system	Auxiliary winding	Frequency	60Hz
A.V.R voltage regulation	AS440 $\pm$ 1.0%	Winding number	Winding 311
Protection	IP 23	Telephone interference	< 75

Features Genset:

- ◇ Enclosure heavy duty steel, Residential silencer included
- ◇ Enclosure center lifting point, External fuel filling
- ◇ Standard sound attenuation foam, Oil & Coolant Drain Ports
- ◇ Direct flexible engine-alternator coupling
- ◇ Structural steel frame with rubber anti-vibration dampers
- ◇ 76 Gallon double wall sub base fuel tank
- ◇ Capacity for 35 hours of autonomy at 100% load prime
- ◇ ABB 125A 3 pole manual circuit breaker
- ◇ Voltage Selector Krauss & Naimer position (Y-YY-Z)
- ◇ Lockable lug box and Cam-Lock distribution panels
- ◇ Convenience receptacles with individual breakers
 - (2) 120V 20 Amp GFCI duplex outlets - (Nema 5-20R type)
 - (2) 125/250V 50 Amp, 3 pole, twist lock (Non-Nema 6369)
- ◇ 12V battery, connection cables, battery holder
- ◇ 12V/3A battery charger in control panel
- ◇ Battery disconnect switch, electric fuel level meter
- ◇ Emergency stop switch located on outside of enclosure
- ◇ Manuals and electrical diagrams in digital



Distribution panel (side)

Controller Data:

Equipped with the latest electronic digital control module DSE 6320, it allows the start, control, protection and stop of the generator set in manual and automatic modes. Makes automatic transfer.

Measurements

- ◇ Current of the three phases L1, L2, L3
- ◇ Voltage of the three phases L - L and L - N
- ◇ Energy demand KWh, KVAh, KVAh
- ◇ Active Energy KVAh
- ◇ Power factor
- ◇ Frequency
- ◇ Hours of operation
- ◇ Memory of the last 250 events, description, date and time
- ◇ Active Power KW
- ◇ Reactive Power KVA
- ◇ Oil pressure
- ◇ Coolant temperature
- ◇ Generator phase sequence.
- ◇ Turning speed
- ◇ Battery voltage

Protections

- ◇ Alarm for maintenance activated configured
- ◇ High engine temperature
- ◇ Low/High frequency
- ◇ Low oil pressure
- ◇ Low/High battery voltage
- ◇ Low/High generator voltage
- ◇ Boot failure
- ◇ Stop failure
- ◇ Negative phase sequence fault
- ◇ Over current fault
- ◇ Overload failure
- ◇ Emergency stop

Enclosed Genset Dimensions:



Noise Level
reference @ 23ft

Maximum
60 + 2 dBA

Ambient
50 dBA

Lenght 84.6 in
Width 43.3 in
Height 64.8 in
Weight 2866 lbs (dry)
Fuel tank 76 gallon (double wall)
Ø Esc. 3 in

Note: reference values, request more detail with dimensional drawing

Application images:



Connection Cam-Lock Standard



Control panel and breaker (rear side)



Lockable external fuel fill